

## Minx Xi Digital Music System

Sept 2013



- Network music player
- Music streaming from computer/NAS/USB
- 20,000 internet radio stations
- High quality Class AB amplifier delivering 2 x 40W RMS
- Wolfson WM8728 DAC
- S/PDIF and Toslink digital audio inputs
- RCA and 3.5mm analogue audio inputs
- Gapless playback supported
- Audiophile grade oversize toroidal transformer
- Free Stream Magic Apple/Android app giving full control of unit
- Supplied with BT100 Bluetooth receiver, allowing audio to be streamed from any paired aptX or A2DP Bluetooth device
- High quality removable speaker terminals allowing use of speaker cable or 4mm banana plugs
- Available in gloss black and white finishes

## Detailed Specifications

<b>Power output</b>	40 watts RMS (into 8 ohms) 47 watts RMS (into 6 ohms) 55 watts RMS (into 4 ohms)
<b>DAC</b>	Wolfson WM8728
<b>Connectivity</b>	Network music playback (Wi-fi & Ethernet), 16-24-bit 32-96kHz 2 x local USB media inputs, 16-24-bit 32-96kHz Toslink input, 16-24-bit 32-96kHz S/PDIF input, 16-24-bit 32-96kHz BT100 Bluetooth receiver: A2DP plus aptX 2 x RCA analogue inputs 3.5mm analogue input Headphone output Speaker outputs, 2 x 40W RMS Subwoofer output
<b>Audio formats supported</b>	ALAC, WAV, FLAC, AIFF, WMA, MP3, AAC, HE AAC, AAC+, OGG
<b>Standby power consumption</b>	<0.5W
<b>Max power consumption</b>	300W
<b>Mains inlet voltage</b>	100-120V AC or 220-240V AC
<b>Dimensions (H x W x D)</b>	90 x 270 x 285mm (3.5 x 10.6 x 11.2")
<b>Weight</b>	5.8kg (12.8lbs)



# Minx Xi Digital Music System